




Customer to tie terminals 2+3 and 4+5 on PC board.

Application of the transformer allows for the leadwires between terminals 2&3 and 4&5 to solder bridge.



Wire insulation & RoHS status not affected by wire color. Wire insulation color may vary depending on availability.

ļ		57112	Method: Tray PKG-0807
ŀ			www.we-online.com/midcom
Ì	6A	6/17	SEE REVISION SHEET FOR REVISION LEVEL

REV. DATE Packaging Specifications

Tolerances unless otherwise specified: Angles: ±1° Decimals: ±.005 [.13] Footprint: ±.001 [.03] Fractions: ±1/64

P.C. PATTERN, COMPONENT SIDE

This drawing is dual dimensioned. Dimensions in brackets are in millimeters.

DRAWING TITLE

TRANSFORMER

eiSos p/n: 750343351

ELECTRICAL SPECIFICATIONS @ 25°C unless otherwise noted:

PARAMETER		TEST CONDITIONS	VALUE
D.C. RESISTANCE	2-4	tie(2+3, 4+5), @20°C	0.400 ohms max.
INDUCTANCE	2-4	tie(2+3, 4+5), 10kHz, 100mVAC, Ls	500.00uH ±10%
SATURATION CURRENT	2-4	tie(2+3, 4+5), 20% rolloff from initial	6A

GENERAL SPECIFICATIONS:

OPERATING TEMPERATURE RANGE: -40°C to +125°C including temp rise.

PART NO.

750343351



SPECIFICATION SHEET 1 OF 1